

Paging Systems ARAS 601 and 602
Paging Systems ARAS 618 and 628
Radio Paging Systems ARAS 651 and 652



Basic Components

Paging System	ARAS 601	ARAS 602	ARAS 618	ARAS 628	ARAS 651	ARAS 652
Display Board AT 961	1 Piece	-	1 Piece	-	1 Piece	-
Display Board AT 962-1314	-	1 Piece	-	1 Piece	-	1 Piece
Control Console BP 301	1 Piece	1 Piece	-	-	-	-
Control Console BP 908	-	-	1 Piece	1 Piece	-	-
Radiokey FT 501	-	-	-	-	1 Piece	1 Piece
Control Unit SE 533	1 Piece	1 Piece	-	-	-	-
Control Unit SE 560	-	-	1 Piece	1 Piece	-	-
Radio Control Unit FSE 550	-	-	-	-	1 Piece	1 Piece
Mains Adaptor NT 500	1 Piece	1 Piece	1 Piece	1 Piece	1 Piece	1 Piece

Additional control consoles or radiokeys and display boards are possible.

Display Board AT 961

1 line with a 3-digit paging number

high contrast red 7-segment-LED digits, 100 mm tall, range of sight circa 40 m

adjustable electronic **2-tone chime**

robust metal casing, silver grey, Dimensions: W 422 x H 174 x D 39 mm

brackets for wall or ceiling mounting,

break-proof low reflection red acrylic glass front,

connection cable with modular (western) plug and socket

Display AT 962-1314

Technically equipped like AT 961

2 lines, upper line with **3-digits paging number**

lower line with **1-digit changeable room or counter number**, Option: up to 4-digits possible

Fixed lettering between lines: "in room no." or "to counter no." or similar.

Dimensions: W 422 x H 374 x D 39 mm

Control Console BP 301

with 1 key "Next", 1 LED control light

Metal casing, silver-grey, Dimensions: W 86 x L 65 x H 25 mm

with 3 m connection cable and modular (western) plug (other cable lengths possible)

directly connected with the analogous input of the display board

Control Console BP 908

electrical, with 4-digits LCD monitor display (18 mm high) for displaying paged numbers

Key pad 0-9, delete key, **"Next" key** (for paging continuous numbers)

5 functional keys for set start number, repeat, postpone (store) wait numbers, report, how many visitors are waiting, block wait ticket dispenser WM 921

Emergency call to other consoles

Programming functions, e.g. of room or counter numbers

6 LED control lights for: Ready state display, **Paging** in process, **Pause** (no visitors waiting),

End of Roll, **Ticket dispenser** barred, **Ticket dispenser** fault

Acoustic signal when 1st visitor draws ticket from waiting ticket dispenser

Metal casing, greyish-white, Dimensions: W 195 x L 145 x H 30 (19) mm

with 3 m connection cable and Western equipment plug (other cable lengths possible)

Control Console BP 902

as BP 301, but electrical, possible additional with ARAS 418 and 438

Acoustic signal when 1st visitor draws ticket from waiting ticket dispenser WM 921, when there are no more visitors waiting or at emergency call

Radiokey FT 501

with 1 key "Next", 1 LED control light, incl. battery plastic casing, grey, Dimensions: W 43 x L 73 x H 19 mm

Control Unit SE 533

integrated into a display, incl. standard software

with 3 analogous inputs for up to 3 different room- or counternumbers

an analogous input can be connected with several consoles parallel with the same room- or

counter number (if 2 parallel consols are pushed at the same moment, only 1 call has been registered)

Control Unit SE 560

integrated into a display, incl. standard software, for up to 8 control consoles and 3 displays

Radio Control Unit FSE 550

integrated into a display, incl. standard software, with radio receiver for up to 8 radiokeys

Mains Adaptor NT 500

with 230 V plug and modular (western) plug

Alterations to incorporate recent technical developments reserved. 07/05

ARAS Paging Systems